

Pulse & Drive Transformers - Families 118, 119

Code	n	Vt [mVs]	I _{max} [mA]	t _r [μs]	R _c [Ω]	C _k [pF]	U _{is} [Vrms]	U _p [Vrms]	Drawing
TI 118010	2 : 1	2,5	1000	1	10	45	500	3100	118E
TI 118020	2 : 1	10,0	400	10	25	65	500	3100	118E
TI 118030	4 : 1	6,0	400	5	25	50	500	3100	118E
TI 118040	1,5 : 1	20,0	400	20	47	50	500	3100	118E
Code	n	Vt [mVs]	I _{max} [mA]	t _r [μs]	R _c [Ω]	C _k [pF]	U _{is} [Vrms]	U _p [Vrms]	Drawing
TI 119010	4 : 1	5,0	400	2	25	40	750	5000	119G
TI 119020	2 : 1	5,0	400	2	25	40	750	5000	119H
TI 119030	2 : 1	10,0	400	5	25	50	750	5000	119G
TI 119040	4 : 1	2,5	400	1	25	50	750	5000	119G

